

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3850-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R213			RK73FB2A824J	CHIP R 820K J 1/10W		
R214			R92-0670-05	CHIP R 0 ΩHM		
R216			RK73FB2A682J	CHIP R 6.8K J 1/10W		
R217, 218			RK73FB2A103J	CHIP R 10K J 1/10W		
R219			RK73FB2A105J	CHIP R 1.0M J 1/10W		
R220, 221			RK73FB2A103J	CHIP R 10K J 1/10W		
R222			R92-0670-05	CHIP R 0 ΩHM		
R223, 224			RK73FB2A223J	CHIP R 22K J 1/10W		
R225, 226			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R227-231			RK73FB2A473J	CHIP R 47K J 1/10W		
R232			RK73FB2A472J	CHIP R 4.7K J 1/10W		
R233			RK73FB2A473J	CHIP R 47K J 1/10W		
R235			RK73FB2A473J	CHIP R 47K J 1/10W	KMK3M3	
R236			RK73FB2A473J	CHIP R 47K J 1/10W		
R238			R92-0670-05	CHIP R 0 ΩHM		
R239			R92-0670-05	CHIP R 0 ΩHM	K2K4	
R239			R92-0670-05	CHIP R 0 ΩHM	M2M4	
R241			RK73FB2A473J	CHIP R 47K J 1/10W	K2K3K4	
R241			RK73FB2A473J	CHIP R 47K J 1/10W	M2M3M4	
R243			R92-0670-05	CHIP R 0 ΩHM	KM	
R244			R92-0670-05	CHIP R 0 ΩHM		
R245-250			RK73FB2A473J	CHIP R 47K J 1/10W		
R251			RK73FB2A103J	CHIP R 10K J 1/10W		
R252			RK73FB2A473J	CHIP R 47K J 1/10W		
R253, 254			RK73FB2A102J	CHIP R 1.0K J 1/10W		
R255, 256			RK73FB2A473J	CHIP R 47K J 1/10W		
R257, 258			R92-0670-05	CHIP R 0 ΩHM		
R259			R92-0679-05	CHIP R 0 ΩHM		
R260, 261			RK73FB2A473J	CHIP R 47K J 1/10W		
R262			RK73FB2A103J	CHIP R 10K J 1/10W		
R263			RK73FB2A473J	CHIP R 47K J 1/10W		
R264			RK73FB2A153J	CHIP R 15K J 1/10W		
R265			RK73FB2A682J	CHIP R 6.8K J 1/10W		
R266			RK73FB2A152J	CHIP R 1.5K J 1/10W	KMK2M2	
R266			RK73FB2A152J	CHIP R 1.5K J 1/10W	K3M3	
R266			RK73FB2A272J	CHIP R 2.7K J 1/10W	K4M4	
R267-271			RK73FB2A222J	CHIP R 2.2K J 1/10W	KMK2M2	
R267-271			RK73FB2A222J	CHIP R 2.2K J 1/10W	K3M3	
R267-271			RK73FB2A472J	CHIP R 4.7K J 1/10W	K4M4	
R279			RK73FB2A473J	CHIP R 47K J 1/10W		
R280			RK73FB2A105J	CHIP R 1.0M J 1/10W		
R285			R92-0670-05	CHIP R 0 ΩHM		
VR1			R12-3132-05	TRIM PØT. 47K		
VR2			R12-6423-05	TRIM PØT. 10K		
VR3			R12-6426-05	TRIM PØT. 33K		
VR4			R12-5058-05	TRIM PØT. 100K		
VR5			R12-3126-05	TRIM PØT. 10K		
VR6			R12-3099-05	TRIM PØT. 47K		
VR7			R12-6427-05	TRIM PØT. 47K		
VR201			R05-3452-05	AF VØL(10K)A		
S201-205			S40-1086-05	TAKT SWITCH(MØNI, AUX, REC, SCAN,		
S206			S40-2440-15	PUSH SWITCH(POWER)		
D1			MI308	DIØDE		
D2 -4			1S5184	DIØDE		

E: Scandinavia & Europe K: USA P: Canada W: Europe

U: PX(Far East, Hawaii) T: England M: Other Areas

UE: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

TX-RX UNIT (X57-3850-XX)

PLL (X58-3700-XX)

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
D6			DAN235(K)	DIODE		
D7			1SS181	DIODE		
D8			MI407	DIODE		
D9			MI308	DIODE		
D10 , 11			MA716	DIODE		
D12			DSA3A1	DIODE		
D13			1SS196	DIODE		
D14			1SS226	DIODE		
D15			ERZ-M10DK220	SERGE ABSORBER		
D16			1SS181	DIODE		
D202			1SS226	DIODE		
D203			1SS184	DIODE		
D205			MA716	DIODE		
IC1			KC004	HIC (FM-IF)		
IC2			UPC1241H	IC(AF POWER AMP)		
IC3			KCA03	HIC (MICAMP)		
IC4			NJM78L05UA	IC(VOLTAGE REGULATOR/+5V)		
IC5			LA5010M	IC(LOW SATURATION REGULATOR)		
IC6			KCB06	HIC (DRIVE)		
IC7			MC7808CT	IC(VOLTAGE REGULATORS/ +8V)		
IC201,202			NJM4558M	IC(OP AMP X2)		
IC203		*	78312AGF323-3BE	IC (SIGNALING CPU)		
IC204		*	75112GF-672-3BE	IC (MAIN CPU)		
IC205			CAT35C102KI	IC (EEPROM)		
IC206		*	L78LR05B-FA	IC(VOLTAGE REGULATOR/+5V)		
Q1 , 2			3SK184(S)	FET		
Q3			2SC2714(Y)	TRANSISTOR		
Q4			2SD1757K	TRANSISTOR		
Q5 , 6			2SB1119S	TRANSISTOR		
Q7			DTC114WK	DIGITAL TRANSISTOR		
Q8			DTC144WK	DIGITAL TRANSISTOR		
Q9 , 10			2SC2712(Y)	TRANSISTOR		
Q11 , 12			2SD1757K	TRANSISTOR		
Q13			2SC2712(Y)	TRANSISTOR		
Q14			2SC2759(U23)	TRANSISTOR		
Q15			2SD1406(Y)	TRANSISTOR		
Q16			2SB1302S	TRANSISTOR		
Q17			DTC114WK	DIGITAL TRANSISTOR		
Q18			DTC144EK	DIGITAL TRANSISTOR		
Q201			DTC144EK	DIGITAL TRANSISTOR		
Q202			DTC114EK	DIGITAL TRANSISTOR		
Q203			2SK208(Y)	FET		
S207			W02-0866-05	ENCODER		
Z1			X59-3740-11	SUB UNIT(HPF)		
Z2			X58-3700-10	SUB UNIT(PLL)	KM	
Z2			X58-3700-11	SUB UNIT(PLL)	K2M2	
Z2			X58-3700-12	SUB UNIT(PLL)	K3M3	
Z2			X58-3700-13	SUB UNIT(PLL)	K4M4	
Z3			X59-3130-00	SUB UNIT(APC)		
PLL (X58-3700-XX) -10 : K,M -11 : K2,M2 -12 : K3,M3 -13 : K4,M4						
C1			CK73FB1H223K	CHIP C	0.022UF	K
C4			CK73FB1H102K	CHIP C	1000PF	K
C5			CK73EB1H603K	CHIP C	0.068UF	K

E: Scandinavia & Europe K: USA P: Canada W: Europe

U: PX(Far East, Hawaii) T: England M: Other Areas

UE: AAFES(Europe) X: Australia

▲ indicates safety critical components.

