

MOBILE VHF ANTENNA MODEL - 1151

MEASURE FROM TOP OF ROD AND CUT TO DESIRED FREQUENCY LENGTH

FREQUENCY	NO SPRING	WITH SPRING
134 MHz	52 3/4 INCH	50 3/16 INCH
136	51 3/4	49 13/16
138	51	48 7/16
140	49 15/16	47 1/4
142	49	46 1/8
144	48 1/16	45 1/4
146	47 1/4	44 7/16
148	46 1/4	43 3/8
150	45 1/2	42 11/16
152	44 13/16	41 15/16
154	44	41 1/8
156	43 1/8	40 3/8
158	42 7/16	39 1/2
160	41 3/4	38 3/4
162	40 15/16	38
164	40 3/8	37 3/8
is6	39 11/16	36 11/16
168	39	36
170	38 3/8	35 7/16
172	37 13/16	34 5/8
174	37 3/16	34 1/4